

<b>Main Menu</b>		
<b>L</b>	<b>Listen to Messages</b>	<b>5</b>
<b>RS</b>	<b>Record &amp; Send a Message</b>	<b>77</b>
<b>CM</b>	<b>Check or Delete Message</b> Lets you know if a msg that you sent has been listened to. If not listened to, you can delete it. <i>UX Mail</i> also lets you listen to the msg before you delete it.	<b>26</b>
<b>G</b>	<b>Mailbox Greetings</b> You can have 3 different greetings. <i>UX Mail</i> plays the greeting you select as "active." If Auto Attendant DND is ON, the Auto Attendant does not ring your phone. Callers immediately hear your greeting. If OFF, the Auto Attendant will try your extension. Callers hear your greeting only if you do not answer or are busy.	<b>4</b>
<b>RN</b>	<b>Record Mailbox Name</b> <i>UX Mail</i> will play your mailbox name in the voice prompts instead of your mailbox number.	<b>76</b>
<b>FD</b>	<b>Future Delivery Message</b> <i>UX Mail</i> sends the message on the date and time you specify.	<b>33</b>
<b>PG</b>	<b>PaGing Message</b> When a caller tries to reach you, <i>UX Mail</i> uses the message to page you. If the message is ON, <i>UX Mail</i> pages immediately. If OFF, <i>UX Mail</i> pages only if you do not answer.	<b>74</b>
<b>OP</b>	<b>Mailbox Options</b>	<b>67</b>
<b>TI</b>	<b>Time and Date</b>	<b>84</b>
<b>SA</b>	<b>Sys Admin Options</b> (For Sys Admin Mailboxes only)	<b>72</b>
	<b>Select Listen Mode</b>	
<b>1N</b>	New Messages	<b>16</b>
<b>1S</b>	Saved Messages	<b>17</b>
<b>1H</b>	Held Messages	<b>14</b>
<b>1A</b>	All Messages	<b>12</b>
	These options are also available while listening to a msg.	
<b>X</b>	<b>Exit Mailbox</b>	<b>9</b>

**Voice Mail** lets callers leave recorded messages for you and lets you leave recorded messages for co-workers. Messages get stored in each person's mailbox. To listen to your messages or use other Voice Mail features, you call your mailbox and access the Main Menu. **Automated Attendant** answers your company's calls with a recorded message and gives dialing instructions for callers to follow.

**While listening you can:**

<b>RE</b>	Record REply	<b>73</b>	<b>RL</b>	Reverse Listening Order	<b>75</b>	<b>VU</b>	Turn Volume Up	<b>88</b>
<b>MF</b>	Have Msg Forwarded	<b>63</b>	<b>L</b>	Listen to Next Msg	<b>5</b>	<b>VD</b>	Turn Volume Down	<b>83</b>
<b>MC</b>	Make Call to Sender	<b>62</b>	<b>B</b>	Backup a Few Secs	<b>2</b>	<b>VN</b>	Restore Volume to Normal	<b>86</b>
<b>TI</b>	Get Time, Date, [Sender]	<b>84</b>	<b>BB</b>	Backup to Beginning	<b>22</b>	<b>#</b>	Exit Listen Mode	<b>#</b>
<b>SA</b>	SAve Message	<b>72</b>	<b>G</b>	Go Ahead a Few Secs	<b>4</b>		See also "Select Listen Mode" on the Main Menu	
<b>E</b>	Erase Msg	<b>3</b>	<b>*</b>	Pause/Resume Listening	<b>*</b>			

**While recording you can:**

<b>B</b>	Backup a Few Secs	<b>2</b>
<b>BB</b>	Backup to Beginning	<b>22</b>
<b>*</b>	Pause/Resume	<b>*</b>
<b>E</b>	Erase Recording	<b>3</b>
<b>TI</b>	Hear Time/Date	<b>84</b>
<b>#</b>	End Recording	<b>#</b>

**When done recording you can:**

	Enter mailbox numbers to receive msg, up to 10.	
<b>*N</b>	Specify recipients by name. After you press *N, follow the voice prompts.	<b>*6</b>
<b>**</b>	Erase msg and return to Main Menu.	<b>**</b>

**After entering a mailbox number or name you can:**

	Enter another mailbox number. Or, press N to enter another mailbox name.	
<b>*R</b>	Request a return receipt. As soon as the recipient listens to your msg, <i>UX Mail</i> lets you know by placing a "receipt" in your mailbox. The receipt consists of two parts: the voice prompt " <b>The following return receipt arrived on (date/time) from (name or number),</b> " followed by the msg that was listened to. After you press *R, you can go to the top of this menu.	<b>*7</b>
<b>*U</b>	Tag a message as "urgent" so the message gets priority handling in the recipient's mailbox. Upon logging on to their mailbox, the recipient hears " <b>This is an urgent message</b> " followed by the message.	<b>*8</b>
<b>*C</b>	Tag a message as "confidential." Recipients of confidential messages cannot use the MF command or Auto Forward feature to send the message to another mailbox.	<b>*2</b>
<b>#</b>	Send msg and return to Main Menu.	<b>#</b>
<b>*N</b>	Specify next recipient by the opposite method, then go to the top of this menu.	<b>*6</b>
<b>*</b>	Cancel previous mailbox. If no mailbox recipients remain, go to previous menu. Otherwise, go to the top of this menu.	<b>*</b>
<b>**</b>	Erase msg and go to Main Menu.	<b>**</b>

**Calling Your UX Mail Mailbox and Accessing the Main Menu**

**To call your mailbox from outside the company:**

1. Dial company phone number \_\_\_\_\_.
2. Wait for the Automated Attendant to answer.
3. Dial # and your mailbox number.
  - Optionally dial \* and a co-worker's mailbox number to leave them a message.
  - The codes in your system may be different.

**To call your mailbox from your UX 5000 terminal:**

1. Press Voice Mail key or your VMsg soft key.
  - Optionally press an idle CALL key and dial \*8.
  - From a single line extension, lift handset and dial \*8 instead.

**To access a feature from your mailbox's Main Menu:**

1. Dial the letters shown to the left of the feature name.
  - The corresponding numbers are shown to the right.
  - The letters you dial to access a feature match some of the letters in the feature name.
  - To get a recorded help message at any time, press 0.

**The mailbox options are as follows:**

<b>S</b>	<b>Security Code</b> Changes or erases your mailbox security code.	<b>7</b>	<b>AT</b>	<b>Auto Time-Stamp</b> Plays the msg time, date and sender after the msg.	<b>28</b>
<b>N</b>	<b>Message Notification</b> Calls co-worker or outside number when you get a msg.	<b>6</b>	<b>CW</b>	<b>Call Waiting</b> Lets a caller send beeps to your ext while you are busy on a call.	<b>29</b>
<b>AH</b>	<b>Auto Help</b> Turns some voice prompts on/off.	<b>24</b>	<b>CA</b>	<b>Call Announcing</b> Lets you know who is calling.	<b>22</b>
<b>AF</b>	<b>Auto Forward</b> Copies your msgs to any mailbox you choose.	<b>23</b>	<b>#</b>	<b>Exit Menu</b>	<b>#</b>

**UX Mail Quick Reference Chart**

0913410  
Rev 1, September 16, 2008  
Printed in U.S.A.

